

Products introduction

To congratulate you order project . features as the following:

LED lamp-house :1pcs LED (5W)

automatic mode

sound controller mode

master slave mode

Standard DMX control signal 2 DMX channels .

power supply : AC100V-240V 50/60Hz

Rated Power Consumption :20w

Work environment :indoor 20°C-40°C

outline : 250×250×245mm

packing size: 310×310×295mm

N/W: 3KG G/W: 3.7KG

Installation

- 1、 Fixup it at any place ,but the distance between the magic light and other objects and person should be at least 1m.and ensure fastness well .do safety measure well .the light should earthing safety .
- 2、 DMX512 connections :
Use the signal line DMX512 to connect all the LED controller, through 3-pin XLR"input"and"output" scoket Controller DMX512 signal (1earth,2-,3+)connect as follow. (Note : pls exchange and connect signal 2 and 3 if it can't by control, generic controller don't use this, singnal line should be within 100 meter,prevent others equipment to be disturbed as excess line.
- 3、 Ensure the voltage and frequency of the factory enactment are suit your locate .you can open it after connect it well .

Operation introduction

DMX Channel	DMX Value	Specification
Channel 1	0--104	dimming weak---strong
	105--199	strobe slow---quick
	200--250	shade slow---quick
	251--255	bright
Channel 2	0--9	stop
	10--120	positive rotation slow---quick
	121--124	stop
	125--245	Opposite rotation slow---quick
	246--255	stop

CODE SWITCH CONTROL LIST

CODE NO	1	2	3	4	5	6	7	9	8	10	
controller mode	○	○	○	○	○	○	○	○	○	×	
slave mode	×	×	×	×	×	×	×	×	√	√	
Mastermode	Runnin Byself	LedAll bright	○	○	○	○	√	√	×	√	×
		Ledshade	○	○	○	○	√	×	×	√	×
		Ledstrobe	○	○	○	○	×	√	×	√	×
		LedSpeedone	○	○	√	√	○	○	×	√	×
		LedSpeedtwo	○	○	×	√	○	○	×	√	×
		LedSpeedthree	○	○	√	×	○	○	×	√	×
		LedSpeedfour	○	○	×	×	○	○	×	√	×
		motorspeed one	√	√	○	○	○	○	×	√	×
		motorspeed two	×	√	○	○	○	○	×	√	×
		motorspeed three	√	×	○	○	○	○	×	√	×
		motorspeed four	×	×	○	○	○	○	×	√	×
		Soundcontrolmode	Soundcontrolmode	Ledall bright	○	○	○	○	√	√	√
LedStrobe	○			○	○	○	√	×	√	×	×
LedStrobe	○			○	○	○	×	√	√	×	×
LedSpeedone	○			○	√	√	○	○	√	×	×
LedSpeedtwo	○			○	×	√	○	○	√	×	×
LedSpeedthree	○			○	√	×	○	○	√	×	×
LedSpeedfour	○			○	×	×	○	○	√	×	×

Note: ①√ select:on × select:off ○ select:on or off

②address code dial from 1-9 for DMX control,address code range 1-5

cleaning and repairing

To confirm the power supply have cut off before disconnect the light or repair it ,it is very important to keep the light cleaning .not only can keep the light maximum brightness output but also can prolong their use life . pls use the high quality professional glass and soft cloth to clear up the equipment ,not permission to use the alcohol and organic liquid .clean at least once each year use vacuum dust collector.

Warning

- ◆ Never dismantle and refit the light
- ◆ pls keep the light don't contact water or other kind liquid and metal .
- ◆ Pls keep the light away from the water ,liquid metal products
- ◆ Pls don't put beam of light on the tinder ,the distance between the magic light and tinder should be at least 2m the distance between the magic light and other objects should be at least 0.5m
- ◆ Pls don't orthoptic beam of the magic light ,or it will be hurt your eye .
- ◆ To confirm the power supply have cut off the light before you open and repair the light .