


Channel	DMX Value	Descriptions
1	000-255	Zoom 0-100%
2	000-255	Master dimmer 0-100%
3	000-255	Strobe from slow to fast
4	000-255	Red intensity 0-100%
5	000-255	Green intensity 0-100%
6	000-255	Blue intensity 0-100%
7	000-255	White intensity 0-100%
8	001-255	Color Macro
9	000-010	No function
	011-119	Color step changing
	120-179	Color cross fade
	180-255	Color step changeing + cross fade
10	000-255	Auto program (CH9) speed from fast to slow

SPECIFICATIONS

Source: 19*15W RGBW high power LEDs
 Beam angle: 10°-60°motorized zoom
 0-100% linear dimmer, high speed strobe
 DMX,Auto, Master/Slave
 DMX Channel: 10ch
 IP20 for indoor use only
 Power input: AC100-240V 50/60Hz
 Power consumption:300W max.
 Dimensions: 226*285*380mm
 Weight: 6.5 kg

IMPORTANT INFORMATION!

In order to optimize the recovery and recycling of the materials that old appliances contain and reduce the impact on human health and the environment, ensure that this product is recycled at the end of its life.



FOS PAR ZOOM ULTRA



User Manual

Please read the manual before operating the fixture. This manual contains important information.



WHAT'S INCLUDED

- 1 x FOS PAR ZOOM ULTRA
- 1 x Power cord
- 1 x User Manual

SAFETY NOTES

- The product is for indoor use only.
- Always turn off, unplug power and allow fixture to cool before servicing.
- Ensure that fixture is properly grounded.
- Please keep this User Guide for future consultation.
- Always make sure that you are connecting to the proper voltage and that the line voltage you are connecting to is not higher than that stated on decal or rear panel of the fixture.
- Always disconnect from power before servicing or replacing fuse.
- Make sure power cord is never crimped or damaged.
- Avoid looking directly into the LED light beam at a close distance!

KEY FEATURES

- Source: 19*15W RGBW high power LEDs
- Beam angle: 10°-60°motorized zoom
- 0-100% linear dimmer, high speed strobe
- DMX,Auto, Master/Slave
- DMX Channel: 10ch
- IP20 for indoor use only
- Power input: AC100-240V 50/60Hz
- Power consumption:300W max.

PRODUCT OVERVIEW



19*15W RGBW high power LEDs



Power In & Out Function buttons DMX In & Out

SETUP

AC Power

This product has an auto-switching power supply that works with an input voltage range of 100 to 240 VAC, 50-60Hz.

Mounting

The FOS PAR ZOOM ULTRA is fully operational in any mounting position, hanging upside-down, side mounted, or set on a flat level surface, etc.

IMPORTANT!!! Safety cables must always be used when unit is ceiling or truss mounted. The safety cable must be capable of holding 10 times the weight of the fixture.

OPERATION INSTRUCTIONS

MENU	Address Range	Description
	d001 — d255	DMX address
	r001 — r255	Red intensity
	G001 — G255	Green intensity
	b001 — b255	Blue intensity
	H001 — H255	White intensity
	P000 — P255	Strobe
	F000 — F255	Zoom
	Pr01 — Pr19	Built-in program
	SP01 — SP16	Built-in program speed
	Auto	Auto program
	Rud1	Sound program
	EPO0 — EPO1	
	dP00 — dP01	Display On/Off
	NT47	LED temperature
	dISP — dSIP	Invert display