

TXS-631SET - Wireless Microphone



Multifrequency microphone system, with UHF PLL technology.

- 1 pocket transmitter, 1 tie clip microphone, 1 receiver, 1 plug-in PSU
- True diversity system
- 80 selectable UHF channels (863-865MHz)
- ACT function for transmitting the selected frequency to the pocket transmitter via infrared signal
- Automatic scan
- Volume and squelch controls
- Transmitting power and gain can be adjusted at the pocket transmitter
- Indication for channel, antenna A/B, ACT status and AF audio level (receiver), channel and battery status (pocket transmitter)
- Stable metal housing (receiver)

Licence-free in the EU.

Technical data:

Carrier frequency	: 863-865MHz
Transmitting power	: < 10mW (EIRP)
RF S/N ratio	: 105dB
Audio range	: 50-18,000Hz, \pm 3dB
Dynamic range	: 120dB
THD	: < 0.5%
Audio output	: 350mV/10k Ohm (jack) 25mV/10k Ohm (XLR, bal.)
Operating range	: approx. 30m
Admiss. ambient temp.	: 0-40 °C
Power supply	:
Transmitter	: 2 x 1.5V batt. AA size
Receiver	: via suppl. plug-in PSU
Dimensions	:
Transmitter	: 62x105x25mm
Receiver	: 152x38x120mm
Weight	:
Transmitter	: 88g
Receiver	: 482g
Connections	: 1 x 6.3mm jack, unbal. 1 x XLR, bal.